

TECHNICAL GUIDE SPECIFICATIONS

PowerRide 1

Single Phase, 2.1 to 17 kW

UL924 Emergency Central Lighting Inverter



Perfect Power Systems

1. GENERAL

2. SCOPE:

Central Lighting Inverter specification defines a high reliability single-phase, on-line, solid-state, double conversion, digital signal processing, high frequency pulse width modulated (PWM) system, utilizing IGBTs, hereafter referred to as the "PowerRide 1".

It shall be designed to provide high quality regulated and conditioned AC power to all lighting loads at all times. It shall provide zero transfer time (no break and no transferring at static bypass switch) to battery upon input power loss or disruption. The unit shall be specifically designed to meet UL 924 for emergency lighting applications and provide 90 minutes of battery back up. It shall be suitable for all lighting loads including any combination of electronic and security system, power factor corrected self-ballast Fluorescent, Incandescent, Quartz Re-strike, Halogen, HID and HPS during emergency backup.

System shall be operated from 0 to 100% loading for the minimum of 90 minutes. Upon return of the normal AC utility line, system shall return to normal mode automatically without any interruption of power to the load. The charging system shall recharge the battery within UL 924 requirements while it uses industry distinctive small footprint stackable cabinet design allowing for equipment installation in limited spaces.

1.2 STANDARDS: The UPS shall comply with the following standards:

- A** - CSA certified per UL1778,
- B** - UL 924 and CSA 22.2 No. 107.1.
- C** - UL 924/UL 924A –Life Safety for Emergency Back up Lighting
- D** - FCC rules and regulations, Part 15, subpart j, class A
- E** – NEMA PE-1
- F** – NFPA 101 (Life safety code)
- G** – ANSI C62.41 (IEEE 587)
- H** – ANSI C62.42.45 (Cat. A and B)
- I** – TVSS (UL1449 2nd Edition)

2.0 PRODUCT DESCRIPTION

2.1 APPROVED MANUFACTURERS AND PRODUCT DESCRIPTION

2.1.1 Approved Manufacturer: The Inverter shall be an Emergency Central Lighting Inverter and shall be manufactured by:

PERFECT POWER SYSTEMS

5940 Triumph Street, Los Angeles, CA 90040

Phone: (800) 786-6915, Fax: (800) 246-2346

Power Service – 1 800 797 7782

2.2 Operation

The system shall utilize High Frequency Pulse Width Modulation, digital signal processing for control and monitoring. The system's automatic-overload and short circuit protection of the inverter in normal and emergency operations shall consist of 150% momentary surge capability and 115% overload for 10 minutes. The system protection shall also include a low-battery voltage disconnect to prevent damages to the battery bank. The system shall supply a clean computer grade sinusoidal output waveform with less than 5% total harmonic distortion at full rated load. Dynamic brownout protection will maintain the desired voltage without continuously switching to batteries in low voltage situations up to -15%. The system shall maintain output regulation of less than $\pm 5\%$ at all operating condition except overload and short circuit. The system shall be able to protect its self from internal over-temperature condition in the event of internal overheat condition and issue an alarm under such condition.

System during normal power utility needs to do power factor correction close to unity (1.0 p.f.) to reduce operating cost for the customer while it is charging the batteries.

The system shall consist of circuitry including an automatic, multi-rate, software-controlled charger; self-diagnostic, programmable system testing capabilities a microprocessor-controlled, diagnostic display panel capable of audible alarms and visual displays of all alarm and inverter; a DC to AC converter (inverter); a battery charger that meet UL 924 standard; an AC and DC input protection; a battery-bank sized for the system's runtime requirements and full KW rating at unity power factor; and an RS232 communication interface.

2.3 System Description

2.3.1 Inverter Design Requirements

- **Output Load Capacity:** The continuous output power rating of the UPS shall be [] kW unit @ 1.0 PF.
- **Output Power Upgrade –** unit shall be designed to have a min 20% of the rated power capacity upgradeability without having to change the unit, option specified at the time of ordering.
- **Input Voltage:** [] VAC, – 15% / + 10%
- **Output Voltage -** [] VAC, 1 phase, 2 wires plus-ground
- **Battery Autonomy:** the UPS shall be capable of operating at full load for 90 mininum on battery power, at a temperature of 25 C.
- **Efficiency:** Greater than 90%
- **Battery Type:** valve regulated sealed lead-acid (VRLA) standard, other type of batteries (option) are available

- **Battery Protection:** battery CB, for safe UPS, battery operation and servicing
- **Cable Installation:** conduit entries on the top and both sides of enclosure

2.3.2 AC Input Specifications

- **Input Voltages:** 120 / 208 / 240 / 277 VAC, 2 wires plus ground
- **Frequency:** 60 Hz +/- 5%
- **Input Current:** sinusoidal, close to unity PF under all line/load conditions (**power factor correction**)
- **Input Protection:** contactor, optional input circuit breaker
- **Input Surge Protection:** Transient Voltage Surge Suppressor (TVSS)
- **Transfer Time:** zero no break transfer (unit static transfer must not switch upon input power loss)
- **Slew Rate:** 0.4 Hz/second, maximum
- **Input Power Connections:** hard wired terminal block, optional input cable
- **Number of Wires:** 2 wires plus ground
- **Cable Installation:** conduit entries on the top and both sides of enclosure

2.3.3 AC Output Specification

- **Output Ratings:** 2.1, 3, 3.5, 5, 5.2, 7, 7.5, 8.8, 10, 10.5, 12.5, 14, 15 and 17 kW
- **Output Voltages:** 120 / 208 / 240 / 277 VAC
- **Frequency:** 60 Hz +/- 0.5 Hz
- **Voltage Regulation:** +/- 3% No Load to Full Load, High Line to Low Line (typical)
- **Output Waveform:** sinusoidal
- **Voltage Distortion:** < 5% THD; < 3% Single Harmonic
- **Inverter Overload Capability:** 125% for 10 minutes, 150% surge for 10 seconds
- **Bypass Overload Capability:** 150%
- **Protection:** fault current limited
- **Non-Linear Load Capability:** 100%
- **Crest Factor:** 1 to 3
- **Output Power Connections:** hard wired terminal block, optional output receptacle panel board with NEMA type receptacles and over current protection (max 30 CBs)
- **Output Distribution:** unit shall have an internal or external load center for customer use, eliminating the need for optional distribution
- **Number of Wires:** 2 wires plus ground

2.4 Battery Specifications

- **Standard Run Time:** 90 min at full load

- **Extended Run Time** : as required
- **Battery Type**: sealed, maintenance-free, lead-acid, VRLA (Standard); optional other types are available.
- **Expected Life**: 10 years
- **Charger Ampacity**: per UL 924
- **Float Voltage**: 2.25 V per cell
- **Protection**: circuit breaker in each battery cabinet
- **Wiring**: power cables from the UPS to the battery cabinet shall be provided by the customer, per local code. With multiple battery cabinets, interconnecting cables shall be provided.
- **Nominal DC Link Voltage**: kVA/kW, (dependent on number of batteries). See chart next page
- **Battery Cabinets**: matching battery cabinets, UL 924 listed, NEMA 1, consult factory for other types. The specific UPS and battery cabinet shall be a CSA listed system per UL924, with a minimum of 90 minutes of battery operation under full load conditions.

2.5 QUALIFICATIONS AND QUALITY ASSURANCE

- 2.5.1 Manufacturer's Certification:** A minimum of twenty years experience in the design, manufacture and testing of solid-state UPS is required. The manufacturer shall specialize in manufacturing of on-line, double conversion high frequency UPS modules specified in this document. The manufacturer shall hold a current ISO 9001 certification and shall design the units in accordance with internationally accepted standards.
- 2.5.2 Materials and Assemblies:** All materials and parts in the UPS shall be new, of current manufacture, unused, except for the purpose of factory testing. All active electronic components shall be solid state and designed as to not exceed the manufacturer's recommended ratings and tolerances for ensuring maximum reliability. All IGBTs and other semiconductor devices shall be sealed. All relays shall have dust covers. All incoming parts, modular assemblies and sheet metal shall undergo detailed receiving quality inspection.
- 2.5.3 Factory Testing:** Every unit shipped will have completed a documented functional test of the UPS module and battery system, including a battery discharge test. A copy of the test report shall be available upon customer's request.

2.6 MODES OF OPERATION:

The UPS module shall be designed to operate as an on-line, high frequency (min 10 kHz), high precision PWM conversion, fully automatic system with "no break" transfer time in the following modes:

- 2.6.1 Normal:** During normal operation, utility (or generator) power is Rectify to DC, drawing sinusoidal input AC current at unity power factor under all load conditions. The DC Rectifier supplies DC power to the Inverter and Battery Charger sections. The Inverter shall supply the load at all time without using the energy stored in the battery using high frequency PWM (min.10 kHz) power technology.

- 2.6.2 Emergency:** Upon loss of input power or when power exceeds the specified input limits, the control logic shall allow the inverter to draw energy from the battery without interruption to the load and disconnect the input line. The transfer to battery shall be uninterrupted - "no break" power transfer. The inverter shall supply power from the batteries to the critical load through. The output voltage shall be sinusoidal and within specified limits 5% regulation. If power is not restored before the batteries have been exhausted, the UPS shall completely shutdown - protecting the batteries from possible damage.
- 2.6.3 Recharge:** When utility power is restored and before the batteries are completely exhausted, the UPS shall automatically return to normal operation. This retransfer to normal operation shall be uninterrupted. The battery charger shall automatically recharge the batteries to full capacity. Recharge characteristics must strictly comply with UL924 requirements.
- 2.6.4 Bypass:** In the event of a component malfunction in either the Rectifier/Charger or the Inverter sections, the unit's Static Bypass Switch shall transfer the load to the utility power with no interruption. Bypass mode shall cause alarm indication and initiate output relay dry contacts closure for customer use.
- 2.6.5 Off-Battery:** When the battery is removed for maintenance or the battery breaker is off, the unit will continue to function, meeting all the specified performance parameters with the exception of the power back up time capability.

2.7 SYSTEM DIAGNOSTICS/ALARM

2.7.1 Front Panel LCD Display: Standard, 4 lines x 20 characters back lit, blue LCD display on the UPS for instant indication of UPS status, metering, alarms and battery condition. The display provides easy read-out on 2 standard and 2 optional screens, providing continuous information with scrolling update:

2.7.2 Status Display

2.7.2.1 System Status

- **Standby:** System is performing self-diagnostic.
- **Start up:** Inverter is being started.
- **Normal:** All parameters are acceptable.
- **Problem:** Loss of utility power over load.
- **Failure:** System requires service.

2.7.2.2 System Rating in KVA

2.7.2.3 Battery Buss Voltage Status

- **Battery ok:** Battery voltage is within acceptable range.
- **Battery bad:** Battery voltage is out of range.

2.7.2.4 Input Voltage Status

- **Input ok:** Input voltage and frequency are within acceptable range.
- **Input bad:** Input voltage and/ or frequency is within acceptable range.

2.7.2.5 Battery Charger Status

- **Charger on:** Battery charger is charging or keeping batteries at float voltage.
- **Charger off:** Battery is being charged.

2.7.2.6 System Internal DC Buss

- **DC ok:** DC buss is within acceptable range.
- **DC bad:** DC buss is out of acceptable range.

2.7.2.7 Static By Pass Status

- **On inverter:** Critical load is being powered and protected by inverter.
- **On by pass:** Critical load is being powered from utility power.

2.7.2.8 Inverter Output Status

- **Out ok:** Output is within acceptable range critical load is being powered by inverter.
- **Out bad:** No output is available from inverter and critical load is being powered from utility power.

2.7.3 Metering Display

- Output voltage
- Output power
- Input voltage
- Input current
- DC buss
- Battery voltage
- Battery current (+) Charging (-) Discharging

2.7.4 Events and Alarms screen - Optional

- UPS Events Time/Date stamp up to 50 scrolling events, with freeze function
- Aux. Output CB Trip – up to 20 CBs Trip alarm on 1st priority trip screens,

2.7.5 System Information Screen - Optional

- Minutes on Battery: UPS in battery back up mode, accrued time
- System Hours: UPS in operation, accrued time
- Battery Event: number of times UPS operated in back up mode
- Temp: UPS cabinet temperature

2.7.6 Alarm Relays: Standard, dry contacts signal relays closing for each of the following alarm conditions: Input Fail, On Bypass, Inverter ON, Low Battery, Summary Alarm

2.7.7 Communication Ports: Standard, Two com ports are available, configured for RS232 and 1 for RS485 data transfer. All parameters displayed on front panel shall be available on these ports for remote monitoring

2.7.8 Power Flow Mimic: Optional. A laminated overlay with embedded color LED's. Combines information on front panel display with a graphic power flow visualization for instant load power status recognition

2.8 MECHANICAL DESIGN AND CONSTRUCTION

- 2.8.1 Enclosure:** All system components shall be housed in a single floor mounted small footprint (39"x 18"), freestanding NEMA 1 enclosure. The cabinet should have front access only with two doors and the depth of no more than 18 inch, allowing easy component reach from the front. The enclosure shall have shelves for component separation and clear and accessible layout. Cabinet doors shall require a key for gaining access. Front access only shall be required for safety and expedient servicing, adjustments and installation. The cabinets shall be structurally adequate and have provisions for hoisting, jacking and forklift handling. Enclosure design shall fully comply with UL 1778 for locked door, unauthorized access protection and UL 924 for accidental or unauthorized unit shutdown.
- 2.8.2 Construction:** Only quality, unused material shall be used to build the unit, under strict observance of standards and quality workmanship. The cabinets shall be cleaned, primed and painted matt black. The unit shall be constructed with rigorously tested, burned-in, replaceable subassemblies. Only two electronic subassemblies: heat sink assembly with IGBTs and drivers and control PCBA shall be used for maximum reliability and simple servicing. All printed circuit assemblies shall have plug connections. Like assemblies and like components shall be interchangeable.
- 2.8.3 Earthquake Protection:** The cabinet shall be evaluated for earthquake zone 4 installation, with the addition of optional earthquake brackets.

2.9 COMPONENT DESCRIPTIONS

- 2.9.1 Input Terminal Block:** an input terminal block shall be hard wired, and located in the UPS close to knockouts for incoming power cable for easy installation. The conduit entries shall be located on the top and both sides of the cabinet.
- 2.9.2 Input Circuit Breaker (optional):** a circuit breaker shall be provided and hard wired at the UPS input for protection from the utility line and associated wiring disturbances. An optional, higher KAIC breaker shall be available, and should be specified when required.
- 2.9.3 Input Contactor:** The UPS shall have a line contactor to isolate the rectifier in case of a line problem and allow for a smooth transfer/retransfer to and from bypass.
- 2.9.4 Input Transformer:** An input transformer shall be factory installed inside the standard UPS cabinet within 39" x 18" footprint design. It shall be located in the lower part of the cabinet, with a barrier separating from the electronics section, to provide isolation between the line and the rectifier / inverter circuit.
- 2.9.5 Rectifier:** a solid state circuit design, converting incoming AC power to regulated DC bus voltage for the input to the inverter and battery charger.
- 2.9.6 Inverter:** The inverter shall feature pulse-width modulation (PWM) design utilizing high frequency (15 kHz) switched IGBT's. It shall use a true double conversion system, generating rated AC output from the utility power, or the batteries when in back up mode. The unit shall have a single heat sink and power IGBT's assembly tray for reduced switching noise and maximum reliability. The assembly shall come as a FRU and its design and mounting location shall

be conceived for an easy maintenance. It shall be located on the electronics shelf with direct access, with opened door and can be replaced in app.15 min, using only a screwdriver.

2.9.7 Charger: A separate battery charger circuit shall be provided. It uses the same IGBT's as in the inverter, with constant voltage and current limiting control. The battery float voltage is uP programmable for the applicable kVA and DC bus ratings. Charging current limit is temperature compensated for battery protection. Full recharge of the batteries shall be in full accordance with UL 924. The rectifier, inverter and charger shall be a part of the heat sink, IGBTs and drivers subassembly as part of FRU modular design aimed at increased ease and safety of service.

2.9.8 Static Bypass : 100% rated, Continuous Duty

The bypass serves as an alternative source of power for the critical load when an input line failure or abnormal condition prevents operation in inverter mode. It consists of a fully rated, continuous duty static switch for high-speed transfers and features two back to back SCRs to allow make before break transfer. The design shall include a Manual Bypass Switch, protected within the locked cabinet. It shall be accessible only to authorized personnel, allowing the unit to stay in bypass at all times for safe work on the unit. Manual transfer to bypass shall not cause unit trip, nor transfer into battery back up mode. The static switch shall be able to be powered up by an optional separate power source (generator or other power supply) for dual input capabilities.

2.9.8.1 Transfer to Bypass - will initiate automatically under the following conditions:

- Critical bus voltage out of limits
- Total battery discharge – (for specified back up time w/o damaging batteries)
- Over temperature period expired
- UPS problem

2.9.8.2 Automatic Re-transfer - takes place whenever the inverter is capable of assuming the critical load. It shall be inhibited for the following conditions:

- When transfer to bypass is activated manually or remotely
- UPS problem

2.9.8.3 All Transfers to Bypass shall be inhibited for the following conditions

- Bypass voltage out of limits (+/- 10 % of nominal)
- Bypass frequency out of limits (+/- 3 Hz)

2.9.9 Control Logic: The entire UPS operation shall be performed by the microprocessor controlled logic. All operations, parameters, diagnostics, test and protection routines are firmware controlled, compensating component drift and changes in operating environment to ensure stable and consistent performance. A self-test and diagnostics subroutine shall assist in troubleshooting the unit. Control PCB shall be located on the front door, removed from power wiring and switching devices. This arrangement shall minimize EMI and allow hot boards swap, in manual bypass mode.

2.9.10 Manual Maintenance Bypass Switch: An auto/man MBS switch shall be provided in the UPS cabinet for connecting power to the critical load through the external maintenance bypass line. It shall be used when the unit needs to be de-energized for maintenance, without disrupting power to the load. Operating the

switch shall be strictly restricted to authorized personnel with cabinet access key. The MBS shall be operated in conjunction with a S-1 synchronization switch, ensuring full synchronization and no inrush current during transfer.

- 2.9.11 Output Transformer:** An isolation output transformer shall be utilized to provide specified output voltage and separate the UPS rectifier/Inverter section from the load disturbances and conducted noise.
- 2.9.12 Manual Inverter Test Switch:** Unit shall have a momentary test switch to allow the user a manual system test without the need to operate any breakers or shutting down the system. The test switch shall be in compliance with UL924 rules, well marked, accessible only after opening a locked front cabinet door and further protected from accidental activation. The PowerRide shall resume a normal operation after the test switch release.
- 2.9.13 Battery Subsystem:** Sealed, maintenance-free VRLA batteries shall be provided. The batteries shall have an expected life of 10 years or a minimum 250 complete discharge cycles. The batteries shall be contained in a separate battery cabinet with a dedicated circuit breaker (no fuses) for battery protection, convenient power cut-off, and servicing. Battery run time (based on 100% full load) shall be no less than the specified time. Runtime shall comply with UL924 providing a minimum of 90 minutes at full load. Specified extended runtimes shall be provided only as an option.

2.10 ACCESSORIES (OPTIONAL COMPONENTS)

- 2.10.1 External Manual Bypass Switch:** If specified by the customer, The bypass switch, enclosed in a box, could be field mounted in the UPS cabinet or an adjacent wall. This box includes a rotary switch with make before break contacts to provide a single control for transferring to and from maintenance bypass with no load support interruption.
- 2.10.2 Audio Alarm with Silence Switch:** Provides audible warning signal, acknowledge and reset for Input Fail, On Bypass, Inverter On, Low Battery and Summary Alarm for any of the foregoing alarm conditions.
- 2.10.3 Remote UPS Status Panel:** The Remote Status Panel is available in a console mount style box in black finish. It can also be wall mounted and comes with a 10 ft long "DB" connector signal cable or optional cable that can be up to 1000 feet long. Remote Status Panel requires 120 VAC power, comes with 6 ft power cord, Silence, LED /Horn test switches. It includes following LED's: Input Fail, On Bypass, Inverter On, Low Battery, Summary Alarm.
- 2.10.4 Form "C" Relay Contacts:** Terminal strip TB is provided on the optional alarm relay board for user connection to the individual alarm contacts. The Remote Contact Board includes isolated Form C contacts for the same signals as on the Remote UPS Status Panel.
- 2.10.5 External Status Indicator:** customer use, N/O volt-free contacts compatible with IBM AS400 standard shall be provided on a plug-in standard connector for the following signals: **Low Battery, On Bypass, Summary Alarm and Input Fail**
- 2.10.6 Normally On/ Normally Off Output Aux. Circuit Breakers:** These CB's are 1 pole, 20 A devices for protection of customer's load circuits. Combine 5.7 & 5.8 to eliminate the need of internal output breakers

- 2.10.7 External Output Aux. CB's In Panel Board:** 1 pole, 20 A located in external panel board mounted on the UPS cabinet side. Maximum number of QO breakers – 42
- 2.10.8 EMI Filter:** complies with: EN55022, 1998 Class "B" Radiated Emission EN55022, 1998 Class "B" conducted emission. FCC Part 15 Class "B" radiated emission, FCC Part 15 Class "B" conducted emission.
- 2.10.9 Higher KAIC Norm On/Off Output CB:** 1 Pole, 20 A Circuit Breaker with Higher KAIC, DIN rail mounted or molded case design.
- 2.10.10 Seismic Mounting Brackets:** Left / Right seismic floor mounting brackets
- 2.10.11 Stackable Rack:** floor space saving solution (1 rack per 2 cabinets)
- 2.10.12 Battery Monitoring System:** single jar, string and entire system monitoring on a local, remote or web enabled PC. Assessment of actual remaining charge and jars deterioration for maximum battery life and total back up safety.
- 2.11 Optional Global Monitoring System (GMS):** All GMS items are optional. The GMS shall allow for flexibility in local and remote communications including internet access
- 2.11.1 Local On UPS Display**
- **Event Log:** Monitoring uP circuit acquires system data and displays up to 50 most recent Date/Time stamped events on the front panel display. Its key-selectable menu provides access to events, system information, display, freeze and delete functions.
 - **Aux. CBs Trip Monitor with Event Log:** In addition to the event log and system data, this option registers trips of up to 20 auxiliary output circuit breakers for monitoring of dedicated circuits. Trip signals from the breakers are displayed on a CB trip screen. Trip modules mount easily on a DIN rail with aux.CB's.
- 2.11.2 Local On PC - Via RS232 or RS485 Port:** This option requires a PC and LabView monitoring software on a Windows platform. Data sent to PC's is displayed as a control room panel for real-time monitoring. The distance to PC for RS232 cable shall be 25 – 150 ft, RS485 increases the range to 1000 ft
- 2.11.3 Remote Dial Up- Monitor 2000:** The Monitor 2000 requires a phone line for remote operation. The device shall send data, voice and text messages to 32 destinations like phone, fax, pager and e-mail via phone line DSL service. The Manager 2000 Windows software installed on a remote PC displays UPS parameters, events and stats graphs. The device shall be installed in the unit and comes fully wired and function-tested
- 2.11.4 Web/SNMP Card:** This option is a web enabled monitoring device for a unit with Internet or network connection. The internal IP internet address can be pre-installed in firmware to fit customer network settings. The SNMP/Web card can monitor the UPS on the network through a standard web browser. A Network Management System software with Alarm Viewer utility shall provide monitoring of multiple units on a single console application.

2.12 Maintenance, Service and Enhanced Warranty Plans:

- 2.12.1 Service Personnel:** The UPS manufacturer shall employ a nationwide service organization, with factory-trained Customer Service Engineers dedicated to the start-up, maintenance, and repair of UPS and power equipment. The manufacturer shall provide a fully automated national dispatch center to coordinate field service personnel schedules. One toll-free number shall reach a qualified support person 24hrs/day, 7days/week and 365 days/year. For emergency service calls, response time from a local Customer Engineer shall be approximately 15 minutes.
- 2.12.2 Replacement Parts:** Parts shall be available through an extensive network to ensure around-the-clock parts availability throughout the country. Customer Support Parts Coordinators shall be on-call 24hrs/day, 7days/week, 365 days a year for immediate parts dispatch. Parts shall be delivered to the site within 24 hours.
- 2.12.3 Maintenance Training:** In addition to the basic operator training conducted as a part of the system start-up, class-room courses for customer employees shall be made available by the manufacturer. The course shall cover UPS theory, location of subassemblies, safety, battery considerations and UPS operational procedures. It shall include AC/DC and DC/AC conversion techniques as well as control and metering, Troubleshooting and fault isolation using alarm information and internal self-diagnostics interpretation shall be stressed.
- 2.12.4 Maintenance Contracts:** A comprehensive offering of preventive and full service maintenance contracts shall be available. An extended warranty and preventive maintenance package shall be available. All services shall be performed by factory trained Service Engineers.
- 2.12.5 Site Testing:** The manufacturer's field service personnel shall provide site testing if requested. The testing shall consist of a complete test of the UPS system and the associated accessories supplied by the manufacturer. A partial battery discharge test shall be provided as part of the standard start-up procedure. The test results shall be documented, signed, and dated for future reference.

NOTE: This Guide Specification follows the Construction Specification Institute guidelines per CSI MP-2-1,MP-2-2. It is subject to change due to product improvement and/or enhancement.

Please use this document as a guide specification, and do not hesitate to contact our application engineering department, should you have any further questions or special requirements.

You can contact us at: **800-786-6915**, or via e-mail:

sales@perfectpowersystems.com, tech@perfectpowersystems.com

2.12.6 WARRANTY

- 2.12.6.1 Inverter Module:** The Inverter manufacturer shall warrant the Inverter against defects in materials and workmanship for a period of twenty-four (24) months. The warranty shall cover all parts and labor for one (1) year period beginning from the start up, or 18 months from the ship date, whichever comes first. Optional 1 year extended warranty and maintenance contract packages shall also be available at the end of the factory maintenance period.

2.12.6.2 Battery: Battery manufacturer's standard warranty shall be transferred and assigned to the end user. It will have a minimum period of ten (10) years.

3.0 Execution

3.1 Physical Specifications

Cabinet shall be double door, floor mountable, fork liftable, black painted with max 18" depth to maximize front accessibility.

Cabinet shall be no more than 40" width for best layout (book shelf style)

Cabinet height shall not exceed 80" to allow pass through standard door.

KW	Input/Output Voltages	MODEL NUMBERS	DC Volts	BTU/ Hr	**Cabinet Size UPS (Battery) (W x H x D)	**Weights (lbs)
2.1	120/120	PD3.0A0100NI-VA	96	859	39" x 48" x 18"	826
	208/208	PD3.0B1300NI-VA		859		826
	240/240	PD3.0D0400NI-VA		859		826
	277/277	PD3.0R2500NI-VA		859		826
	120, 208, 240, or 277	**PD3.0X5800TI-VA		1166		896
3.0	120/120	PD3.0A0100NI	96	1227	39" x 48" x 18"	996
	208/208	PD3.0B1300NI		1227		996
	240/240	PD3.0D0400NI		1227		996
	277/277	PD3.0R2500NI		1227		996
	120, 208, 240, or 277	**PD3.0X5800TI		1433		896
3.5	120/120	PD5.0A0100NI-VA	96	1314	39" x 68" x 18"	1101
	208/208	PD5.0B1300NI-VA		1314		1101
	240/240	PD5.0D0400NI-VA		1314		1101
	277/277	PD5.0R2500NI-VA		1314		1101
	120, 208, 240, or 277	**PD5.0X5800TI-VA		1433		1171
5.0	120/120	PD5.0A0100NI	120	1875	39" x 68" x 18"	1214
	208/208	PD5.0B1300NI		1875		1214
	240/240	PD5.0D0400NI		1875		1214
	277/277	PD5.0R2500NI		1875		1214
	120, 208, 240, or 277	**PD5.0X5800TI		2047		1284
*5.25	208/208	PD7.5B1300NI-VA	120	1973	51" x 70" x 30.5"	1506
	240/240	PD7.5D0400NI-VA		1973		1506
	277/277	PD7.5R2500NI-VA		1973		1506
	208, 240, or 277	**PD7.5X5800TI-VA		2150		1666
	208/208	PD010B1300NI-VA		192		2629
240/240	PD010D0400NI-VA	2629	1867			
277/277	PD010R2500NI-VA	2629	1867			
208, 240, or 277	**PD010X5800TI-VA	2866	2042			
208/208	PD7.5B1300NI	120	2819		51" x 70" x 30.5"	2190
240/240	PD7.5D0400NI		2819	2190		
277/277	PD7.5R2500NI		2819	2190		
208, 240, or 277	**PD7.5X5800TI		3070	2350		
208/208	PD012B1300NI-VA		192	3287		51" x 70" x 30.5"
240/240	PD012D0400NI-VA	3287		2352		
277/277	PD012R2500NI-VA	3287		2352		
208, 240, or 277	**PD012X5800TI-VA	3583		2572		
208/208	PD010B1300NI	192		3755	51" x 70" x 30.5"	
240/240	PD010D0400NI		3755	2695		
277/277	PD010R2500NI		3755	2695		
208, 240, or 277	**PD010X5800TI		4094	2870		
208/208	PD015B1300NI-VA		240	3926		51" x 70" x 30.5"
240/240	PD015D0400NI-VA	3926		2792		
277/277	PD015R2500NI-VA	3926		2792		
208, 240, or 277	**PD015X5800TI-VA	4299		3132		
208/208	PD012B1300NI	192		4696	51" x 70" x 30.5"	
240/240	PD012D0400NI		4696	3557		
277/277	PD012R2500NI		4696	3557		
208, 240, or 277	**PD012X5800TI		5118	3777		
208/208	PD020B1300NI-VA		240	5257		51" x 70" x 30.5"
240/240	PD020D0400NI-VA	5257		4172		

*14	208/208	PD020B1300NI-VA	240	5257	51" x 70" x 30.5"	4172
	240/240	PD020D0400NI-VA		5257		4172
	277/277	PD020R2500NI-VA		5257		4172
	208, 240, or 277	**PD020X5800TI-VA		5732		4172
*15	208/208	PD015B1300NI	240	5608	51" x 70" x 30.5"	4172
	240/240	PD015D0400NI		5608		4172
	277/277	PD015R2500NI		5608		4172
	208, 240, or 277	**PD015X5800TI		6141		4172
*17	208/208	PD017B1300NI	240	5608	51" x 70" x 30.5"	4172
	240/240	PD017D0400NI		5608		4172

* Consult factory for 120V input units and other power ratings.

3.2 Installation

The Central Lighting Inverter shall be installed in accordance with all appropriate manufacturer's installation instructions and in compliance with all appropriate codes.

3.3 ENVIRONMENTAL REQUIREMENTS

- **Operating Temperature:** - 0 C to 40 C (32 F to 104 F)
- **Storage Temperature:** - 20 C to +45C (- 4F to 113 F)
- Maximum recommended storage temperature for batteries is 77 F for up to six months. Storage at up to 104 F is acceptable for a maximum of three months.
- **Humidity: operating and storage:** 0 to 95% RH, non condensing
- **Altitude:** up to 6000 ft (1,829 meters)
- **Audible Noise:** 57 dB typ. on "response curve A"

3.4 Wiring Installation: UPS cabinet conduit entry arrangement shall allow for flexibility of user wiring installation. The wiring shall be routed thru the top or either side of the cabinet.

3.5 Wiring Termination: The UPS input and output power connections shall be hard wired within the cabinet. Optional input line cable and output receptacle panels shall be available (limited range of units only, please consult factory for details). Input and output terminal blocks shall be provided for easy field wiring of UPS and battery cabinets

3.6 System Operation:

The system shall allow connection of both "normally on" or "normally off" loads. Connected loads shall be carried via the transfer circuit by the utility during normal operation or by the system inverter during utility failures without interruption.

3.7 Connected Loads

The Central Lighting Inverter system shall be designed to maintain the normal operation and performance integrity of all connected loads including voltage and frequency sensitive equipment by providing true "no break", continually conditioned sinusoidal output. Refer to plans for type and location of loads server by the system.

3.8 Drawings and manuals

Drawings and manuals supplied with each unit shall include: Complete set(s) of shop drawings showing physical dimensions, mounting information and wiring diagrams. Installation Manual(s) with complete instructions for locating, mounting, interconnection and wiring of the system.

User Manual(s) outlining complete operating and preventive maintenance procedures.

3.9 Factory Startup

Provides a factory service representative to perform the initial startup of the Central Lighting Inverter System.